

This Page Is Inserted by IFW Operations
and is not a part of the Official Record

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images may include (but are not limited to):

- BLACK BORDERS
- TEXT CUT OFF AT TOP, BOTTOM OR SIDES
- FADED TEXT
- ILLEGIBLE TEXT
- SKEWED/SLANTED IMAGES
- COLORED PHOTOS
- BLACK OR VERY BLACK AND WHITE DARK PHOTOS
- GRAY SCALE DOCUMENTS

IMAGES ARE BEST AVAILABLE COPY.

**As rescanning documents *will not* correct images,
please do not report the images to the
Image Problem Mailbox.**

THIS PAGE BLANK (USPTO)

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
10 April 2003 (10.04.2003)

PCT

(10) International Publication Number
WO 03/030478 A1

(51) International Patent Classification⁷: **H04L 25/03, H04B 7/005, 1/12**

(21) International Application Number: **PCT/US02/25848**

(22) International Filing Date: **14 August 2002 (14.08.2002)**

(25) Filing Language: **English**

(26) Publication Language: **English**

(30) Priority Data:
09/956,443 19 September 2001 (19.09.2001) US

(71) Applicant (for all designated States except US): **ERICSSON, INC. [US/US]; 7001 Development Drive, Research Triangle Park, NC 27709 (US).**

(72) Inventors; and

(75) Inventors/Applicants (for US only): **ARSLAN, Huseyin [TR/US]; 3022 Quail High Blvd., Morrisville, NC 27560 (US). KHAYRALLAH, Ali, S. [US/US]; 113 Streamview Drive, Apex, NC 27502 (US).**

(74) Agent: **PHILLIPS, Steven, B., et al.; Moore & Van Allen, PLLC, 2200 West Main Street, Suite 800, Durham, NC 27705 (US).**

(81) Designated States (national): **AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NO, NZ, OM, PH, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, YU, ZA, ZM, ZW.**


(84) Designated States (regional): **ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE, SK, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).**

Published:

— with international search report

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(54) Title: **METHOD AND APPARATUS FOR CANCELLING CO-CHANNEL INTERFERENCE IN A RECEIVING SYSTEM USING SPATIO-TEMPORAL WHITENING**



(57) Abstract: Methods and apparatus for canceling co-channel interference in a receiving system using spatio-temporal whitening. In some embodiments, a spatio-temporal interference canceling method, and apparatus for carrying out the method are provided which effectively cancel co-channel interference despite frequency offset between the desired signal and the interferer in a TDMA type system. Real and imaginary component values of the total received signal are used for virtual diversity branches, and a vector-valued auto regressive model (402, 1302) is used to characterize the interference. In other embodiments, spatio-temporal interference whitening (1603, 1703) is used to improve timing estimates used for synchronization. The two uses of spatio-temporal whitening can be combined in one receiver. The invention is typically implemented in one or more programmed digital signal processors or application specific integrated circuits (ASICs), embodied in a receiving system.

WO 03/030478 A1

METHODS AND APPARATUS FOR CANCELING CO-CHANNEL INTERFERENCE IN A RECEIVING SYSTEM USING SPATIO-TEMPORAL WHITENING

DESCRIPTION

Background Art

A receiver that needs to demodulate a desired signal in a communication system must always deal with extracting the desired signal from noise. At one time, so-called "white noise" presented the greatest concern. White noise is characterized in that the noise "signal" is random, or uncorrelated, in time and space, meaning that the amplitude, phase, and other measurable characteristics of the noise at any one time or place cannot be used to predict the characteristics at any other time and place. Methods of designing a receiver to deal with white noise are well-known and have been in existence for decades.

Modern communication systems, such as wireless time domain multiplexed access (TDMA) systems increasingly have to deal with so-called "colored noise" which is correlated and has predictable characteristics. Co-channel interference is one example of colored noise. Co-channel interference has become a significant problem as the population density of people using wireless, cellular communication devices increases. Because of the traffic demand, it is necessary to re-use channels more frequently on a geographic basis. Co-channel interference can cause problems in different sections of a TDMA receiver. Such interference can cause difficulty with the timing estimation used for synchronization in the initial stage of processing a received signal. It can also create errors filtering and demodulating the signal in subsequent stages.

FIG. 1 illustrates the received signal at wireless terminal 101 where there is both co-channel interference and white noise present. Base station 102 is transmitting a desired signal over a channel designated C_d and base station 103 is transmitting an interfering signal or "interferer" over a channel designated C_i . Other interference is simply referred to as "noise" n . Given that each channel has specific characteristics that are represented with complex valued quantities, the total received signal at wireless terminal 101 can be represented as:

$$r = C_d \otimes S_d + C_i \otimes S_i + n,$$

where S_d is the desired signal and S_i is the interferer. Note that r is complex valued even where the signals, S_d and S_i are real-valued. FIG. 2 illustrates the spectrums of the desired signal and the interferer, 201 and 202 respectively, in the frequency domain.

5 One known way to deal with co-channel and other colored interference in communication systems is to use some type of whitening filter to "whiten" the interference, so that the desired signal now only needs to be distinguished from white noise. Temporal whitening involves removing temporal correlation from the interfering signal and requires knowledge of the interfering signal's characteristics
10 at different points in time. Spatial whitening involves removing spatial correlation from the interfering signal and requires knowledge of the interfering signal's characteristics at different points in space. True, spatial whitening in wireless systems requires multiple antennas. A signal is said to have a different "diversity branch" for each antenna. The two types of whitening can be combined, resulting in whitening in both time and space, commonly called "spatio-temporal" whitening. With
15 any kind of whitening, knowledge of the characteristics of the channel is also needed to extract and demodulate the desired signal from the whitened signal.

In TDMA systems, such as those that implement the well-known *Global System for Mobile* (GSM), *General Packet Radio Service* (GPRS), and *Enhanced General Packet Radio Service* (EGPRS) standards and their various incarnations,
20 a signal is received as a stream of timeslots. Each timeslot contains a known training sequence, also called a "sync word." FIG. 3 illustrates such a timeslot, with training sequence, 301. Since the contents of the training sequence is known, the characteristics of the desired and interfering signals can be isolated in time and space, and used for spatio-temporal whitening just prior to demodulating
25 the desired signal, using multiple antennas to perform the spatio-temporal whitening. Co-channel interference is also a problem for mobile terminals. However, since only one antenna is available, spatial or spatio-temporal whitening is difficult. Additionally, spatio-temporal whitening just prior to demodulating does not
30 increase synchronization accuracy in the presence of co-channel interference.

Disclosure of Invention

In some embodiments of the invention, interference in a received signal is cancelled prior to demodulation by determining spatio-temporal, time-varying whitening filter parameters and time-varying channel parameters based on a frequency offset between an interferer and a desired signal. One way to determine the time-varying parameters is to determine fixed parameters first and then rotate them using the frequency offset. The filter parameters are applied to the received signal to obtain a whitened signal. The whitened signal is then demodulated using the time-varying channel parameters. Co-channel interference is effectively canceled despite any frequency offset between the interferer and the desired signal. Prefiltering is provided using the time-varying channel parameters if needed. Time-varying whitening filter and channel parameters can also be determined by sampling portions of timeslots in the received signal and updating the parameters for each selected portion. In this case, co-channel interference is effectively canceled despite any frequency offset or slot misalignment between the interferer and the desired signal.

In another embodiment, the entire received signal is de-rotated using the frequency offset between the desired signal and the interferer. Time-invariant whitening filter parameters and initial channel parameters are determined, in TDMA systems, using the training sequence of the timeslot of interest. The time-invariant whitening filter parameters are used to whiten the received signal over the timeslot prior to demodulation to produce the whitened signal. Time-varying channel parameters for demodulation and prefiltering are obtained by rotating the initial channel parameters with the frequency offset.

In other embodiments, synchronization is improved by including spatio-temporal whitening in the timing estimation process in the interference whitening synchronization block or synchronization and initial channel estimation block of a receiver. In this case a plurality of signal samples is produced for a portion of the received signal, typically, the training sequence. They may be produced either by decimating to reduce the number of samples per symbol, or they may be produced by first applying a timing estimation method without spatio-temporal whitening. In any case, spatio-temporal interference whitening is applied to each of

the plurality of signal samples to produce a plurality of whitened signal samples. The best sample is determined from the whitened signal samples based on channel estimates and on a relative, minimum value of a specified metric. The receiver is synchronized based on this best sample. The synchronization with spatio-temporal whitening may be applied to all signals receiver, or it may be selectively applied only when needed, depending on the channel-to-noise ratio achieved with a more traditional, less computationally intensive method.

Apparatus to carry out the invention is typically implemented in one or more programmed digital signal processors or application specific integrated circuits (ASICs). The apparatus that carries out the invention may include synchronization logic using spatio temporal interference whitening (STIW). The synchronization logic may include a decimator and a selection system to determine the best sample to use for synchronization from a plurality of samples. The apparatus also may include a single antenna interference rejection (SAIR) block that determines the channel parameters and filter parameters. These blocks may be combined. In one embodiment, the SAIR block applies the whitening filter to the received signal based on a frequency offset between the desired signal and an interferer. Demodulation logic demodulates the whitened signal using the channel parameters. The demodulation logic in some embodiments includes either decision feedback sequence estimation (DFSE) or maximum likelihood sequence estimation (MLSE). Prefiltering may also be provided.

The invention can be embodied in any receiving system, including, but not limited to: a wireless terminal having a single antenna; a base station with a single antenna; or processing circuitry that deals with the signal at a single antenna in a larger system using multiple antennas, whether a base station, mobile terminal or other receiving system. In the case of a TDMA based mobile terminal, the invention can be embodied in baseband logic that is operatively connected to a radio block and a main processor system.

Brief Description of Drawings

FIG. 1 is a network block diagram that illustrates an operating environment in which co-channel interference is present.

FIG. 2 is a frequency domain graph illustrating co-channel interference.

FIG. 3 illustrates a known TDMA timeslot having a training sequence, otherwise known as a sync word.

FIG. 4 is a high-level block diagram of a receiving system according to some embodiments of the invention.

FIG. 5 is another high-level block diagram of a receiving system according to other embodiments of the invention.

FIG. 6 is a flowchart illustrating the interference rejection method according to one embodiment of the invention.

FIG. 7 is a block diagram of a single-antenna interference rejection (SAIR) block used in a receiving system according to an embodiment of the invention.

FIG. 8 is another flowchart illustrating the interference rejection method according to an embodiment of the invention.

FIG. 9 is another block diagram of a single-antenna interference rejection (SAIR) block used in a receiving system according to an embodiment of the invention.

FIG. 10 is another flowchart illustrating the interference rejection method according to an embodiment of the invention.

FIG. 11 illustrates slot misalignment as handled during interference canceling according to one embodiment of the invention.

FIG. 12 is another flowchart illustrating the interference rejection method according to an embodiment of the invention.

FIG. 13 is another block diagram of a receiving system according to an embodiment of the invention.

FIG. 14 is another block diagram of a single-antenna interference rejection (SAIR) block used in a receiving system according to an embodiment of the invention.

FIG. 15 illustrates the general concept of sampling a portion of a received signal to estimate timing for course synchronization.

FIG. 16 is a block diagram showing a interference whitening synchronization block for a receiving system according to an embodiment of the invention.

FIG. 17 is another block diagram showing another interference whitening synchronization block for a receiving system according to an embodiment of the invention.

FIG. 18 is a flowchart illustrating the process of timing estimation according to an embodiment of the invention.

FIG. 19 is another flowchart illustrating the process of timing estimation according to another embodiment of the invention.

FIG. 20 is a block diagram of a receiving system illustrating certain aspects of a timing estimation method according to an embodiment of the invention.

FIG. 21 is a block diagram of a receiving system illustrating certain aspects of a timing estimation method according to another embodiment of the invention.

FIG. 22 is a block diagram of a wireless terminal which can embody the invention.

Best Mode(s) for Carrying Out the Invention

The present invention is typically embodied in a receiving system for a communication network employing time domain multiplexed access (TDMA). The embodiments disclosed are not restricted to any particular standard, however. As previously mentioned, the well-known Global System for Mobile (GSM) communication system is one example of a TDMA system which might employ the invention. The timeslot illustrations shown herein are based on GSM. However, differences in these timeslot arrangements, such as including the training sequence in some other part of the timeslot, will not affect the operation of the invention.

It should also be understood that not every feature of the receiving system described is necessary to implement the invention as claimed in any particular one of the appended claims. Various elements of receivers are described to fully enable the invention. It should also be understood that throughout this disclosure, where a process or method is shown or described, the steps of the method may be performed in any order or simultaneously, unless it is clear from the context that one step depends on another being performed first.

Some of the block diagrams and flowcharts, which are used to illustrate the inventive concepts, are not mutually exclusive. Rather, each one has been tailored to illustrate a specific concept discussed. In some cases, the elements or steps shown in a particular drawing co-exist with others shown in a different drawing, but only certain elements or steps are shown for clarity. For example, the synchronization methods using spatio-temporal whitening can be used independently in the same receiving system with another independent single-antenna interference whitening (SAIR) block just prior to demodulation and/or prefiltering.

The invention includes the application of improved uses of spatio-temporal whitening in at least two places in a TDMA type receiving system. Figures 4 and 5 present high-level block diagrams illustrating these uses. FIG. 4 illustrates a receiving system including a first stage, 401, which is a synchronization and channel estimation logic block according to the prior art. SAIR 402 is a single-antenna interference rejection block, according to the invention, which offers improved performance in the presence of co-channel interferer which exhibits a frequency offset as compared to the desired signal. The system of FIG. 4 also includes a prefilter 403 and a decision feedback sequence estimation (DFSE) block, 404. The DFSE performs demodulation using estimated channel parameters. These elements receive a received signal and produce soft values for the received symbols to be further processed by parts of the receiving system which are known to those of ordinary skill in the art and which are omitted for clarity.

FIG. 5 illustrates embodiments where spatio-temporal whitening is included in the synchronization and channel estimation logic according to the invention. Joint synchronization and spatio-temporal interference whitening (STIW) block 500 is also referred to herein as an "interference whitening synchronization block" to distinguish it from the synchronization and channel estimation logic of the prior art shown in FIG. 4. Prefilter 503 and DFSE block 504 are essentially the same as shown in FIG. 4. It should be noted that the interference whitening synchronization block, or joint synchronization and STIW block, 500, as shown in FIG. 5 can make use of any kind of spatio-temporal interference whitening (STIW) filter. The SAIR discussed throughout this disclosure is one particular type of STIW. The interference whitening synchronization block of the invention can use SAIR, and in

effect, combine the functions of the SAIR block in FIG. 4 with the functions of the joint synchronization and STIW block of FIG. 5. It is also possible to have two SAIR functions, one in block 500 of FIG. 5, and a separate one placed as shown in FIG. 4. However for synchronization with interference whitening according to the invention, any kind of STIW will do.

A brief overview of the concept of separating a signal into virtual diversity branches based on real and imaginary parts follows. The Single Antenna Interference Rejection (SAIR) algorithm is an algorithm that enables interference rejection with only one antenna. The algorithm concentrates on real-valued modulation schemes, such as binary phase shift keying (BPSK) and Gaussian minimum shift keying (GMSK). Such an algorithm can be implemented as an equalizer based on maximum likelihood sequence estimation (MLSE), or on decision feedback sequence estimation (DFSE). The main difference between MLSE and DFSE is that DFSE requires a prefilter which must be taken into account in the whitening filter matrix. The real and imaginary parts of the signal are referred to as the I and Q channels, respectively. Additionally, a SAIR algorithm models the noise and interference as a vector-valued auto regressive (VAR) process in order to design a finite impulse response (FIR) matrix whitening filter.

A better model of the complex signal r previously discussed is represented by the equation:

$$\tilde{r}(n) = \sum_{m=0}^L \tilde{h}(m)s(n-m) + \tilde{v}(n),$$

where $\tilde{h}(m)$ is the complex-valued channel impulse response of length $L+1$, $s(n)$ is sent symbols and $\tilde{v}(n)$ denotes the additive noise and interference. Splitting the above equation into real and imaginary parts to separate the I and Q channels yields:

$$r(n) = \begin{bmatrix} r_I(n) \\ r_Q(n) \end{bmatrix} = \sum_{m=0}^L \begin{bmatrix} h_I(m) \\ h_Q(m) \end{bmatrix} s(n-m) + v(n).$$

Note that since $s(n)$ is real-valued, it can be estimated from both the real and imaginary parts of the received signal.

The noise and interference is modeled as a VAR process by the following

equation:

$$v(n) = \begin{bmatrix} v_I(n) \\ v_Q(n) \end{bmatrix} = \sum_{k=1}^K A_k \begin{bmatrix} v_I(n-k) \\ v_Q(n-k) \end{bmatrix} + e(n),$$

where A_k is the matrix of VAR coefficients,

$$A_k = \begin{bmatrix} a_{11}(k) & a_{12}(k) \\ a_{21}(k) & a_{22}(k) \end{bmatrix}, \quad 1 \leq k \leq K,$$

5 and where the noise vector,

$$e(n) = \begin{bmatrix} e_I(n) \\ e_Q(n) \end{bmatrix},$$

is assumed to be white and Gaussian.

Given the above, a matrix FIR whitening filter with coefficients W_k can be designed as:

$$10 \quad W_k = \begin{cases} A_k & \text{for } k > 1 \\ I & \text{for } k = 0 \end{cases}.$$

The whitened signal then becomes:

$$r_w(n) = \sum_{k=0}^K W_k \sum_{m=0}^L \begin{bmatrix} h_I(m) \\ h_Q(m) \end{bmatrix} s(n-m-k) + \sum_{k=0}^K W_k v(n-k).$$

Applying the VAR equation yields:

$$r_w(n) = \sum_{i=0}^{L+K} \begin{bmatrix} b_I(i) \\ b_Q(i) \end{bmatrix} s(n-i) + e(n),$$

15 where $b(i)$ denotes the channel after whitening. The noise is now temporally white and uncorrelated.

In order to obtain uncorrelated elements of the noise $e(n)$, I/Q noise decorrelation is performed according to:

$$\bar{r}_w(n) = D r_w(n),$$

20 where D is a matrix with the property,

$$Q^{-1} = D^T D.$$

The matrix D is calculated using a Cholesky factorization scheme, ultimately resulting in:

$$\bar{r}_w(n) = \sum_{i=0}^{K+L} \left[\frac{\bar{b}_I(i)}{\bar{b}_Q(i)} \right] s(n-i) + \bar{e}(n),$$

where $\bar{e}(n)$ is a white zero mean noise vector with mutually uncorrelated elements and where $\bar{b}(i)$ is the channel impulse response after whitening and I/Q noise decorrelation. In practical application, the VAR matrix A_k , the covariance matrix Q , and $b(i)$ can be estimated using an indirect, generalized least squares method.

In the above discussion, it is assumed that the interferer does not have any frequency offset or timeslot misalignment as compared to the desired signal. In this case, the whitening filter parameters are obtained over the synch word of a timeslot and applied to the received signal for the whole timeslot. If there is frequency offset in the interfering signal, the optimal whitening filter parameters will change over time, as the interfering signal will be rotated depending on the amount of the frequency error. Therefore, if the parameters that are obtained for the whitening filter over the synch word as shown above are applied to the whole received signal, the frequency offset may reduce some of the performance gain that could otherwise be obtained. Slot misalignment between the interfering signal's timeslots and the desired signal's timeslot can have a similar effect.

There are several ways the SAIR can be improved to take into account the frequency offset of a co-channel, interfering signal. If the frequency offset of the interferer is known, time-varying whitening filter parameters including the matrix coefficients can be obtained. Time-varying channel parameters can also be obtained. These time-varying parameters can be obtained directly. Alternatively, the initial whitening filter coefficients and channel coefficients can be obtained as described above, discounting frequency offset, and then the coefficients can be updated by rotating them using the knowledge of the frequency offset. Coefficients are updated in each direction from the sync word as follows:

$$\begin{aligned} a'_{11}(n) &= a_{11} \cos^2(2\pi f_0 n) + a_{22} \sin^2(2\pi f_0 n) - (a_{12} + a_{21}) \cos(2\pi f_0 n) \sin(2\pi f_0 n) \\ a'_{12}(n) &= a_{12} \cos^2(2\pi f_0 n) + d_{21} \sin^2(2\pi f_0 n) - (a_{11} + a_{12}) \cos(2\pi f_0 n) \sin(2\pi f_0 n) \\ a'_{21}(n) &= a_{21} \cos^2(2\pi f_0 n) + d_{12} \sin^2(2\pi f_0 n) - (a_{11} + a_{22}) \cos(2\pi f_0 n) \sin(2\pi f_0 n) \\ a'_{22}(n) &= a_{22} \cos^2(2\pi f_0 n) + a_{11} \sin^2(2\pi f_0 n) - (a_{12} + a_{21}) \cos(2\pi f_0 n) \sin(2\pi f_0 n) \end{aligned}$$

where a_{ij} is the (ij) th element of the whitening filter parameter matrix A .

The original channel parameters that were obtained only over the sync word can be updated as:

$$b(n) = [\Gamma \cdot \Psi(n)] \cdot D'(n),$$

5 where, for a second order VAR process,

$$\Gamma = \begin{bmatrix} h_1^T & 0 & 0 \\ h_1^T & h_2^T & 0 \\ h_1^T & h_2^T & h_3^T \\ \vdots & \vdots & \vdots \\ h_{L-2}^T & h_{L-1}^T & h_L^T \\ 0 & h_{L-1}^T & h_L^T \\ 0 & 0 & h_L^T \end{bmatrix} \quad \Psi(n) = \begin{bmatrix} A'_0(n) \\ A'_1(n) \\ A'_2(n) \end{bmatrix}.$$

The prefilter coefficients are calculated based on the initial channel estimates over the sync word and can be fixed over the whole timeslot. Note that the whitening filter parameters do not change considerably for each consecutive sample for more reasonable amounts of frequency offset (in the range of 200-500 Hz). Therefore, updating the parameters might not be necessary at each sampling point in every situation. It may be sufficient to divide the timeslot into segments and update the parameters on a segment-by-segment basis, thus reducing the computational complexity. How often such an update is needed depends on the amount of the frequency offset.

FIG. 6 is a high-level flowchart of these embodiments of the invention. At step 601, time-varying whitening and channel parameters are estimated, typically based on the training sequence, taking into account a known-frequency offset. At step 602, the time varying whitening filter parameters are applied to the whole timeslot. At step 603, the timeslot is demodulated using the time varying channel parameters.

FIG. 7 is a block diagram of the SAIR block according to the present embodiment. Initial channel and whitening filter parameters are estimated at 701 based on the training sequence in a sampled, received signal. These parameters are then rotated by rotation block 702 using the frequency offset of the interferer. Spatio-temporal whitening using the time-varying parameters resulting from the

rotation is applied by the whitening filter, 703, and a whitened signal is produced. Time-varying channel parameters are also produced and passed along to the pre-filter and demodulation logic of the receiver system.

FIG. 8 illustrates the process carried out by the apparatus of FIG. 7 in another flowchart. At step 801 the initial whitening and channel parameters are determined. At step 802 these parameters are rotated to obtain time-varying parameters. At step 803 they are applied via the filter to whiten the entire received timeslot. At step 804 the timeslot is demodulated using the time varying channel parameters.

Another way to account for frequency offset in the SAIR is to de-rotate the received signal based on the frequency offset. The received signal with a frequency offset in the interferer is given by:

$$\bar{r}(n) = \sum_{m=0}^L \bar{h}(m)s(n-m) + \bar{v}(n)e^{j2\pi f_0 n}.$$

The de-rotated signal can be written as:

$$\bar{r}'(n) = \bar{r}(n)e^{-j2\pi f_0 n} = e^{-j2\pi f_0 n} \sum_{m=0}^L \bar{h}(m)s(n-m) + \bar{v}(n),$$

which becomes,

$$r'(n) = C(n) \sum_{m=0}^L h(m)s(n-m) + v(n).$$

Now, the interferer does not have a frequency offset, but the desired signal has a frequency offset. The channel taps for the desired signal can be rotated in time accordingly. The SAIR algorithm can be used without accounting for the frequency offset for the whitening filter parameters. Time-varying channel parameters will still have to be obtained as before. Applying the whitening filter in this case results in:

$$r'_w(n) = D \left[\sum_{k=0}^K W_k C^H(n-k) \sum_{m=0}^L h(m)s(n-m-k) \right] + De(n).$$

FIG. 9 illustrates an embodiment of the invention where the frequency offset is accounted for by de-rotating the received signal. De-rotation is accomplished at block 901 based on the frequency offset of the interferer, before application of the SAIR. Thus, the frequency offset of the interferer is eliminated.

Therefore, the interferer is time-invariant, however, the desired signal is time-varying. Whitening filter parameters and channel parameters are estimated using the training sequence at block 902. Since the interferer does not change, constant whitening filter parameters that are obtained over the training are applied to the whole received slot by spatio-temporal whitening filter 903. However, the channel estimates of the desired signal are rotated according to the original frequency offset of the interferer. Therefore, according to this embodiment, the whitening filter parameters are constant over the whole slot, but the desired signal's channel parameters will be time-varying. Both the fixed whitening filter parameters and fixed channel parameters can be obtained over the training. The channel parameters are then rotated accordingly to obtain the correct time varying channel parameters.

FIG. 10 illustrates the process just discussed in flowchart form. At step 1001 the received signal is de-rotated. At step 1002, time-invariant whitening filter parameters are obtained. Channel parameters are also obtained over the training sequence. At step 1003, time-invariant whitening filter parameters are applied to the entire timeslot. At step 1004 the channel parameters are rotated. At step 1005 the estimated channel parameters are used to demodulate the timeslot.

Another alternative for providing the SAIR function in the presence of a frequency offset can be used if the frequency offset is unknown and not easy to estimate. In this embodiment, the whitening filter parameters are tracked over the data portion of the timeslot. Tracking can be done continuously or on a portion-by-portion basis. For the tracking, estimated data is initially used. The prefilter parameters are calculated over the synch word and applied to the received signal. With such tracking, slot-misaligned cases can also be handled. When the impairment characteristics change, parameters can be updated. FIG. 11 illustrates a slot-misaligned situation. As can be seen, interferer slot 1101 is delayed relative to desired signal slot 1102.

FIG. 12 illustrates the method just described in flowchart form. To accomplish the tracking, a SAIR with fixed parameters is applied over the synch word to calculate the initial whitening filter parameters and channel parameters, as shown at step 1201. At 1202 the first portion of the timeslot is set to the "new portion".

At 1203, the whitening filter using the initial parameters is applied. At 1204, the new portion is demodulated using the channel parameters. Prefiltering is also applied if needed. At 1205 a test is made to determine if the demodulation of the timeslot is complete. If so, the process stops. If not, whitening filter and channel parameters for the next portion, if there is one, are estimated from the current portion at 1206. The next "new portion" is retrieved at 1207.

FIG 13 shows a block diagram of the pertinent parts of a receiving system implementing the embodiment discussed with respect to FIG. 12. Synchronization and channel estimation logic 1301 are present as before. SAIR block 1302 obtains the whitening filter parameters and desired signal's channel parameters over the training sequence, which are output at 1303. The whitening parameters are applied to a portion of the slot just after the synch word, then this portion of the slot is demodulated through prefilter 1304 and DFSE block 1305 using the whitened samples and the channel parameters of the desired signal. The demodulated symbols over this portion of the slot are used to estimate new whitening filter and channel parameters. The new whitening parameters are applied to each new portion of the timeslot by SAIR block 1306 to obtain the whitened samples for this portion and the process continues likewise. SAIR block 1302 and SAIR block 1306, though logically separate, may be in fact implemented by the same SAIR logic.

FIG. 14 shows a more detailed block diagram of SAIR block 1306 of FIG. 13. Since the signal is being supplied to the SAIR block and a portion-by-portion basis, there is no channel or signal rotation. This SAIR block is similar to a SAIR block that might be used in a system that does not take frequency offset into account, except that the whitening filter and channel estimation block 1401 operates on each new block, not just on the training sequence. Spatio-temporal whitening filter 1402 is applied using the estimated filter parameters to produce a whitened signal.

Other embodiments are now described in which STIW is applied to the timing estimation performed in the synchronization logic of a receiver. The application of spatio-temporal interference whitening at this stage can increase channel-to-noise ratio by determining the best timing offset with which to receive the

symbols being sent in a timeslot. As is well-known, synchronization logic in TDMA receivers performs course synchronization first, followed by fine synchronization. It is assumed that course synchronization is first performed before the interference whitening synchronization block by a traditional method. The synchronization method that makes use of STIW that is described in detail here is for fine syn-

chronization.

Fine synchronization according to the invention finds the best reference point (among all possible reference points determined in a coarse synchronization) for the down-sampling and demodulation of the received samples. Finding the correct reference point is very important to the signal-to-noise-ratio (SNR) of the received signal, sometimes referred to as channel-to-noise (C/N) ratio in a TDMA system. FIG. 15 illustrates how course synchronization is accomplished what a timeslot looks like just before fine synchronization according to the invention. 1501 illustrates the timeslot before any synchronization, showing symbols S-5 through S5. 1500 shows the same timeslot after course synchronization. A course sampling and timing hypothesis, 1502, showing samples 1, 2, 3, . . . N, one sample per symbol, results from the course synchronization. 1503 shows different potential sampling points within a symbol. Fine synchronization will need to determine which of these sampling points is best.

Before describing these embodiments of the invention in detail, it is useful to discuss one known, conventional way of performing fine synchronization (or timing estimation). Assume that the coarse synchronization reduced the possible number of symbols to +/- K symbols, and assume that for each symbol there are M sampling position (for example 8 samples per symbol). Therefore, the total number of sampling hypotheses is $(2K + 1)M$. Further, assume that for each sampling position hypothesis, the received signal is down-sampled to one sample per symbol, resulting in $r_k(n)$ received samples for the kth sampling position hypothesis. A least square channel estimation is performed using the knowledge of the synch word. Using the estimated channel parameters, \hat{H}_k and the known synch sequence, S, a replica of the received samples is calculated as $\hat{r}_k(n)$. The difference between what is received and what is modeled is calculated by:

$$e_k = \frac{1}{N} \sum_{n=1}^N |r_k(n) - \hat{r}_k(n)|^2$$

where N is the length of the synch sequence. This timing offset estimate minimizes the error among all possible timing hypotheses.

According to the invention, both interference cancellation and timing offset estimation are done jointly within the synchronization logic. For the interference cancellation part of the process a spatio-temporal interference whitening (STIW) approach is employed. The STIW used in the synchronization can be SAIR as previously described, or other types of STIW, including STIW using multiple antennas.

A block diagram of an interference whitening synchronization block using STIW is shown in FIG. 16. The logic of FIG. 16 is normally located in block 500 of FIG. 5. This timing estimation can be independently applied to any receiver structure, or to any equalization scheme. FIG. 16 only shows one of these applications. Similarly, application of STIW in the timing offset estimation process does not necessarily require the use of STIW before equalization. It is possible to apply STIW only for the timing offset estimation, and perform equalization without whitening the received samples. A typical receiver includes the blocks that preprocess the received antenna signal (signal preprocessor). Typically, the preprocessor includes receiver filtering, amplifiers, and mixers that produce baseband signal. The received signal shown in all of the figures herein is the preprocessed signal.

FIG. 16 shows a block diagram of the joint timing offset estimation and interference whitening that is sometimes referred to herein as interference whitening synchronization. The received samples are decimated by decimator 1601 based on sample timing from the sample timing selector, 1602, to obtain the down-sampled received samples (usually one sample per symbol). The down-sampled received samples (around the training region) are passed through STIW block 1603. The output of the STIW block is the whitened received samples $z_k(n)$. In this embodiment, channel estimates \hat{C}_k are passed through the same whitening filters. The filtered channel estimates and the known training sequence $s(n)$ are

used to calculate a replica of the whitened received samples $\hat{z}_k(n)$. This calculation is performed in metric calculator block 1604. The difference between what is received and what is modeled is calculated as:

$$e_k = \frac{1}{N} \sum_{n=1}^N |z_k(n) - \hat{z}_k(n)|^2.$$

5 The calculated metric value from above is passed to the metric comparator and minimum metric selector block, 1605. This block compares all the calculated metric values corresponding to all the sample timing positions and finds the minimum metric value. The minimum metric value and the corresponding sample timing position is selected as the estimated sample timing position. The sample timing selector knows all the possible timing hypotheses, and one-by-one, provides the timing positions to the decimator. The sample timing selector knows whether there is another sample timing position to evaluate. Since the sample timing selector, 1602, is connected to the minimum metric selector, when all the hypotheses are evaluated, the sample timing selector provides the timing hypotheses that has the minimum metric to the decimator, 1601. The sample time selector 1602 may also be connected to the STIW block, 1603 to indicate that this is the best timing position and stop the process. This connection is represented by the dotted arrow in FIG. 16.

Decimator 1601 decimates the oversampled signal. Starting from the decided timing position, it selects one (or more) samples from each symbol. The decimator does not need to decimate the entire timeslot to test all the hypotheses. Only training samples are used. At the end of the process, when the best timing offset has been selected, the decimator may decimate the whole timeslot. The STIW algorithm in block 1603 may then operate on the decimated samples, calculating the vector valued whitening filter parameters and whitening all the received samples.

FIG. 17 is a block diagram for the case where the receiver performs spatiotemporal whitening only for the timing offset estimation, and does not apply whitening to the whole received signal. Returning to Figures 4 and 5, FIG. 17 would represent the case where block 500 of FIG. 5 does not actually combine the functions

algorithms. A conventional timing estimation is applied first to the received time-slot at step 1901. The channel estimates and the residual error (minimum metric value) are calculated using the estimated timing offset at step 1902. The C/N value is calculated from the channel estimates and the residual error value estimate at step 1903. The energy of the combined channel taps provides C , and the residual error provides N . If the estimated C/N value is below a threshold value at decision point 1905, then the joint timing estimation and STIW algorithm is employed at step 1906. Otherwise we use the timing estimates of the conventional algorithm as shown at 1904.

FIG. 20 shows a block diagram of the combined algorithm as described above. A conventional timing estimation is applied first for the received timeslot by block 2001. Then, the channel estimates and the residual error are calculated from the estimated timing offset. If the C/N value is below a threshold value, then timing estimation is switched to the joint timing estimation and STIW algorithm implemented in block 2002. Decisions are made by the control unit, 2003. The "other receiver parts," 2004 are as previously described.

Another way of combining the conventional timing estimation with the interference whitening synchronization block implementing joint timing estimation and STIW is to employ the conventional timing estimation to narrow-down the possible timing position choices. Then, joint algorithm can be used to obtain a finer timing estimate. FIG. 21 is a block diagram that also illustrates the signal flow for this embodiment. Assume that initially there are X possible timing offset positions. The conventional algorithm is executed by block 2101 first. From the conventional algorithm, the metric values (residual errors) corresponding to all the timing positions are calculated. These metric values and the initial timing positions are passed through comparator and selector block, 2102, where a group (Y out of X , where $Y < X$) of the smallest metric values and the corresponding timing positions are selected. These selected timing positions are fed to the interference whitening synchronization block, 2103, where the joint timing estimation and STIW algorithm are executed for better tuning. Other receiver parts 2104 are as previously discussed.

Other embodiments could also be devised where timing offset estimation is

done only for some subset of the possible timing hypotheses. For example, for each symbol, a random timing offset can be selected rather than formally hypothesizing timing sample values for each symbol. In this case, the timing offset hypothesis only consists of the different symbol timings, not the samples within the symbols.

As previously discussed, the joint synchronization and STIW approach can be used with either single or multiple antenna receivers. There are various possible extensions of the to the multiple antenna receivers. In multiple antenna receivers, for each antenna element, instead of employing a conventional timing estimation, the proposed interference whitening synchronization algorithm can be employed to get the timing of that antenna element. An independent STIW algorithm (in the I-Q domain) in each antenna element can be combined with spatial whitening across antenna elements. The independent STIW algorithm (in the I-Q domain) in each antenna element can be combined with another STIW algorithm across the antenna elements. Such an algorithm can be performed iteratively by first treating each antenna element independently, then applying STIW in the I-Q domain to get the possible timing estimates. The number of hypotheses can optionally be reduced. STIW is then applied across antennas.

FIG. 22 is a block diagram of a mobile terminal that implements the invention. FIG. 22 illustrates a terminal with voice capability, such as a mobile telephone. This illustration is an example only, and the invention works equally well with mobile terminals that are dedicated to communicating with text or other forms of data. As described above, some embodiments of the invention can also work in base stations designed to communicate with such a mobile terminal. As shown in FIG. 22, the terminal includes radio block 2201, a baseband logic block, 2202, control logic block 2203 and an audio interface block, 2204. Within radio block 2201, the receive and transmit information is converted from and to the radio frequencies (RF) of the various carrier types, and filtering is applied, as is understood in the art. Radio block 2201 includes the preprocessor previously discussed. The terminal's antenna system, 2207, is connected to the radio block. In baseband logic block 2202, basic signal processing occurs, e.g., synchronization, channel coding, decoding and burst formatting. In this example, the base-

band logic includes the SAIR of the invention. The baseband logic block also optionally includes the interference whitening synchronization block according to the invention. Audio interface block 2204 handles voice as well as analog-to-digital (A/D) and D/A processing. It also receives input through microphone 2205, and
5 produces output through speaker 2206. Control logic block 2203, coordinates the
aforedescribed blocks and also plays an important role in controlling the human
interface components (not shown) such as a key pad and liquid crystal display
(LCD). The functions of the aforedescribed transceiving blocks are directed and
controlled by one or more microprocessors or digital signal processors such as
10 main processor 2208, shown for illustrative purposes. Program code, often in the
form of microcode is stored in memory 2209 and controls the operation of the ter-
minal through the processor or processors. The mobile terminal illustrated in FIG.
22 interfaces to a smart card identity module (SIM), 2211, through a smart card
reader interface. The interconnection between the main processor, control logic,
15 memory, and SIM is depicted schematically. The interface is often an internal
bus.

A mobile terminal implementation of the invention does not have to be a
traditional "cellular telephone" type of terminal, but may include a cellular radio-
telephone with or without a multi-line display; a personal communications system
20 (PCS) terminal that may combine a cellular radiotelephone with data processing,
facsimile and data communications capabilities; a personal data assistant (PDA)
that can include a radiotelephone, pager, Internet/intranet access, Web browser,
organizer; and a conventional laptop and/or palmtop computer or other appliance
that includes a radiotelephone transceiver. Mobile terminals are sometimes also
25 referred to as "pervasive computing" devices.

Some embodiments of the invention can be implemented in base station
systems as previously described. An exemplary BSS includes a base station
controller (BSC) and base station transceivers or base transceiver stations (BTS),
each providing service for a single cell through an antenna system. The antenna
30 system can have a single antenna, or multiple antennas. Each BTS includes at
least one transmitter as well as one or more receiving systems that receive time-

slots on uplink frequencies. One or more of these receiving systems embody the invention.

Specific embodiments of an invention are described herein. One of ordinary skill in the networking and signal processing arts will quickly recognize that the invention has other applications in other environments. In fact, many embodiments and implementations are possible. In addition, the recitation "means for" is intended to evoke a means-plus-function reading of an element in a claim, whereas, any elements that do not specifically use the recitation "means for," are not intended to be read as means-plus-function elements, even if they otherwise include the word "means." The following claims are in no way intended to limit the scope of the invention to the specific embodiments described. We claim:

CLAIMS

1. A method of canceling interference over a timeslot of a received signal in a time domain multiplexed access communication system, the method comprising:

- 5 determining spatio-temporal, time-varying whitening filter parameters and time-varying channel parameters for the timeslot based on a frequency offset between an interferer and a desired signal, time-varying, real and imaginary component values of the received signal, and a vector-valued auto regressive model of the interference;
- 10 applying the time varying whitening filter parameters to the received signal over the timeslot to obtain a whitened signal; and
- demodulating the whitened signal over the timeslot using the time-varying channel parameters.

2. The method of claim 1 wherein determining time-varying spatio-temporal whitening filter parameters further comprises:

- 15 determining initial whitening filter parameters and initial channel parameters using a training sequence for the timeslot; and
- rotating the initial whitening filter parameters and the initial channel parameters with the frequency offset to obtain the time varying whitening filter parameters and the time varying channel parameters.
- 20

3. The method of claim 1 wherein demodulating the whitened signal further comprises:

- prefiltering the whitened signal using the time-varying channel parameters; and
- 25 applying decision feedback sequence estimation.

4. The method of claim 2 wherein demodulating the whitened signal further comprises:

- prefiltering the whitened signal using the time-varying channel parameters; and

applying decision feedback sequence estimation.

5. The method of claim 1 wherein demodulating the whitened signal further comprises applying maximum likelihood sequence estimation to the whitened signal.

5 6. The method of claim 2 wherein demodulating the whitened signal further comprises applying maximum likelihood sequence estimation to the whitened signal.

7. A method of canceling interference over a timeslot of a received signal in a time domain multiplexed access communication system, the method comprising:

de-rotating the received signal over the timeslot using a frequency offset between a desired signal and an interferer;

15 determining spatio-temporal, time-invariant whitening filter parameters and time-invariant, initial channel parameters using a training sequence of the timeslot and based on time-varying real and imaginary component values of the received signal and a vector-valued auto regressive model of the interference;

applying the time-invariant whitening filter parameters to the received signal over the timeslot to produce a whitened signal;

20 rotating the initial channel parameters with the frequency offset to
obtain time-varying channel parameters; and

demodulating the whitened signal over the timeslot using the time-varying channel parameters.

8. The method of claim 7 wherein demodulating the whitened signal further
25 comprises:

prefiltering the whitened signal using the time-varying channel parameters; and

applying decision feedback sequence estimation.

9. The method of claim 7 wherein demodulating the whitened signal further comprises applying maximum likelihood sequence estimation to the whitened signal.

5 10. A method of canceling interference over a timeslot of a received signal in a time domain multiplexed access communication system, the method comprising:

10 determining spatio-temporal, whitening filter parameters and channel parameters based on time-varying real and imaginary component values of the received signal and a vector-valued auto regressive model of the interference, and using a training sequence for the timeslot;

applying the whitening filter parameters to the received signal over a selected portion of a plurality of portions of the timeslot to obtain a whitened signal;

15 demodulating the whitened signal over the portion using the channel parameters;

if additional portions of the timeslot remain un-demodulated, updating the whitening filter parameters and the channel parameters based on the selected portion of the timeslot and repeating the applying and demodulating for a new portion of the timeslot.

20 11. The method of claim 10 wherein demodulating the whitened signal further comprises:

prefiltering the current whitened signal using the channel parameters; and

applying decision feedback sequence estimation.

25 12. The method of claim 10 wherein demodulating the whitened signal further comprises applying maximum likelihood sequence estimation to the whitened signal.

13. Apparatus for canceling interference over a timeslot of a received signal in a time domain multiplexed access communication system, the apparatus comprising:

means for determining spatio-temporal, time-varying whitening filter parameters and time-varying channel parameters for the timeslot based on a frequency offset between an interferer and a desired signal;

means for applying the time varying whitening filter parameters to the received signal over the timeslot to obtain a whitened signal; and

means for demodulating the whitened signal over the timeslot using the time-varying channel parameters.

14. Apparatus for canceling interference over a timeslot of a received signal in a time domain multiplexed access communication system, the apparatus comprising:

means for de-rotating the received signal over the timeslot using a frequency offset between a desired signal and an interferer;

means for determining spatio-temporal, time-invariant whitening filter parameters and time-invariant, initial channel parameters using a training sequence of the timeslot;

means for applying the time-invariant whitening filter parameters to the received signal over the timeslot to produce a whitened signal;

means for rotating the initial channel parameters with the frequency offset to obtain time-varying channel parameters; and

means for demodulating the whitened signal over the timeslot using the time-varying channel parameters.

15. Apparatus for canceling interference over a timeslot of a received signal in a time domain multiplexed access communication system, the apparatus comprising:

means for obtaining spatio-temporal, whitening filter parameters and channel parameters using a training sequence for the timeslot;

means for applying the whitening filter parameters to the received signal over a selected portion of a plurality of portions of the timeslot to obtain a whitened signal;

5 means for demodulating the whitened signal over the selected portion using the channel parameters;

means for updating the whitening filter parameters and the channel parameters based on each selected portion of the plurality of portions.

16. A method of synchronizing a receiver with a received signal, the method comprising:

10 producing a plurality of signal samples for a portion of the received signal;

applying spatio-temporal interference whitening to each of the plurality of signal samples to produce a plurality of whitened signal samples;

15 determining a best whitened signal sample from among the plurality of whitened signal samples based on channel estimates and on a relative, minimum value of a specified metric for each of the plurality of whitened signal samples; and

synchronizing the receiver based on timing of the best whitened signal sample.

20 17. The method of claim 16 wherein the producing of the plurality of signal samples further comprising decimating a portion of the received signal.

18. The method of claim 16 wherein the producing of the plurality of signal samples further comprises:

25 decimating the portion of the received signal to produce a first group of samples for the portion of the received signal; and

selecting the plurality of signal samples from the first group of samples based on an initial timing estimate made without spatio-temporal whitening.

19. The method of claim 16 wherein the applying of spatio-temporal interference whitening is accomplished at least in part through the use of time-varying channel parameters and whitening filter parameters which take into account a frequency offset between the received signal and an interfering signal.

5 20. The method of claim 17 wherein the applying of spatio-temporal interference whitening is accomplished at least in part through the use of time-varying channel parameters and whitening filter parameters which take into account a frequency offset between the received signal and an interfering signal.

10 21. The method of claim 18 wherein the applying of spatio-temporal interference whitening is accomplished at least in part through the use of time-varying channel parameters and whitening filter parameters which take into account a frequency offset between the received signal and an interfering signal.

22. A method of synchronizing a receiver with a received signal, the method comprising:

15 decimating a portion of the received signal to produce a plurality of signal samples;
 estimating a timing for the received signal based on the plurality of signal samples and on channel estimates without applying spatio-temporal whitening to the plurality of signal samples;
 20 determining if a signal-to-noise ratio of the received signal, received using the timing is below a specified threshold value;
 applying spatio-temporal interference whitening to each of the plurality of signal samples to produce a plurality of whitened signal samples, if the signal-to-noise ratio is below the specified threshold value;
 25 determining a best whitened signal sample from among the plurality of whitened signal samples based on channel estimates and on a relative, minimum value of a specified metric for each of the plurality of whitened signal samples, if the signal-to-noise ratio is below the specified threshold value; and

synchronizing the receiver based on timing of the best whitened signal sample if the signal-to-noise ratio is below the specified threshold value.

- 5 23. The method of claim 22 wherein the applying of spatio-temporal interference whitening is accomplished at least in part through the use of time-varying channel parameters and whitening filter parameters which take into account a frequency offset between the received signal and an interfering signal.

24. Apparatus for synchronizing a receiver with a received signal, the apparatus comprising:

- 10 means for producing a plurality of signal samples for a portion of the received signal;
- means for applying spatio-temporal interference whitening to each of the plurality of signal samples to produce a plurality of whitened signal samples;
- 15 means for determining a best whitened signal sample from among the plurality of whitened signal samples based on channel estimates and on a relative, minimum value of a specified metric for each of the plurality of whitened signal samples; and
- means for synchronizing the receiver based on timing of the best whitened signal sample.

- 20 25. Apparatus for synchronizing a receiver with a received signal, the apparatus comprising:

- means for decimating a portion of the received signal to produce a plurality of signal samples;
- 25 means for estimating a timing for the received signal based on the plurality of signal samples and on channel estimates without applying spatio-temporal whitening to the plurality of signal samples;
- means for determining if a signal-to-noise ratio of the received signal, received using the timing is below a specified threshold value;

means for applying spatio-temporal interference whitening to each of the plurality of signal samples to produce a plurality of whitened signal samples;

5 means for determining a best whitened signal sample from among the plurality of whitened signal samples based on channel estimates and on a relative, minimum value of a specified metric for each of the plurality of whitened signal samples; and

means for synchronizing the receiver based on timing of the best whitened signal sample.

10 26. A processor-controlled receiving system enabled to cancel interference in a received signal, the receiving system comprising:

synchronization and channel estimation logic;

15 a single antenna interference rejection (SAIR) block connected to the synchronization and channel estimation logic, the SAIR block for determining time-varying channel parameters and applying a whitening filter to the received signal based on a frequency offset between the desired signal and an interferer to obtain a whitened signal; and

demodulation logic for demodulating the whitened signal using the time varying channel parameters.

20 27. The receiving system of claim 26 wherein the SAIR block further comprises:

logic for determining initial whitening filter parameters and initial channel parameters for a timeslot in the received signal; and

25 a rotation block for rotating the initial whitening filter parameters and the initial channel parameters with the frequency offset to obtain time-varying whitening filter parameters and the time-varying channel parameters for the timeslot in the received signal.

28. The receiving system of claim 26 wherein the SAIR block further comprises:

a de-rotation block for de-rotating the received signal with the frequency offset; and

logic for determining time-invariant whitening filter parameters and time-varying channel parameters for a timeslot in the received signal.

5 29. The receiving system of claim 26 wherein the demodulation logic further comprises:

a decision feedback sequence estimation (DFSE) block; and

a prefilter disposed between the DFSE block and the SAIR block.

10 30. The receiving system of claim 26 wherein the demodulation logic further comprises a maximum likelihood sequence estimation (MLSE) block.

31. The receiving system of claim 27 wherein the demodulation logic further comprises:

a decision feedback sequence estimation (DFSE) block; and

a prefilter disposed between the DFSE block and the SAIR block.

15 32. The receiving system of claim 27 wherein the demodulation logic further comprises a maximum likelihood sequence estimation (MLSE) block.

33. The receiving system of claim 28 wherein the demodulation logic further comprises:

a decision feedback sequence estimation (DFSE) block; and

20 a prefilter disposed between the DFSE block and the SAIR block.

34. The receiving system of claim 28 wherein the demodulation logic further comprises a maximum likelihood sequence estimation (MLSE) block.

35. A processor-controlled receiving system enabled to cancel interference in a received signal, the receiving system comprising:

25 synchronization and channel estimation logic;

a first single antenna interference rejection (SAIR) block connected to the synchronization and channel estimation logic, the SAIR block for determining channel parameters and applying a whitening filter to the received signal based on a frequency offset between the desired signal and an interferer to obtain a whitened signal;

demodulation logic for demodulating the whitened signal using the channel parameters; and

a second SAIR block connected to the demodulation logic, the second SAIR block for updating the whitening filter parameters and the channel parameters based on each selected portion of a plurality of portions of a timeslot in the received signal.

36. The receiving system of claim 35 wherein the demodulation logic further comprises:

a decision feedback sequence estimation (DFSE) block; and

a prefilter disposed between the DFSE block and the SAIR block.

37. The receiving system of claim 35 wherein the demodulation logic further comprises a maximum likelihood sequence estimation (MLSE) block.

38. A processor-controlled receiving system comprising:

demodulation logic; and

a interference whitening synchronization block preceding the demodulation logic, the interference whitening synchronization block disposed to receive a received signal and further comprising:

a decimator disposed to receive the received signal, the decimator for producing a plurality of signal samples from the received signal;

a timing selector operatively connected to the decimator;

a spatio-temporal interference whitening (STIW) block connected to the decimator, the STIW block for applying spatio-temporal

interference whitening to each of the plurality of signal samples to produce a plurality of whitened signal samples; and

a selection subsystem connected to the timing selector and the STIW block, the selection subsystem operable to determine a best whitened signal sample from among the plurality of whitened signal samples based on channel estimates and on a relative, minimum value of a specified metric and for synchronizing the receiver with the received signal based on timing of the best whitened signal sample.

39. The receiving system of claim 38 wherein the interference whitening synchronization block is selectively enabled to receive the received signal under the control of a control unit.

40. The receiving system of claim 38 further comprising a single antenna interference rejection (SAIR) block disposed between the interference whitening synchronization block and the demodulation logic, the SAIR block for determining time-varying channel parameters and applying a whitening filter to the received signal based on a frequency offset between the received signal and an interfering signal.

41. The receiving system of claim 39 further comprising a single antenna interference rejection (SAIR) block disposed between the interference whitening synchronization block and the demodulation logic, the SAIR block for determining time-varying channel parameters and applying a whitening filter to the received signal based on a frequency offset between the received signal and an interfering signal.

42. The receiving system of claim 38 wherein the STIW block is a single antenna interference rejection (SAIR) block for determining time-varying channel parameters and applying a whitening filter to the received signal based on a frequency offset between the received signal and an interfering signal.

43. The receiving system of claim 39 wherein the STIW block is a single antenna interference rejection (SAIR) block for determining time-varying channel parameters and applying a whitening filter to the received signal based on a frequency offset between the received signal and an interfering signal.

5 44. The receiving system of claim 40 wherein the demodulation logic further comprises:

a decision feedback sequence estimation (DFSE) block; and
a prefilter disposed between the DFSE block and the SAIR block.

10 45. The receiving system of claim 41 wherein the demodulation logic further comprises:

a decision feedback sequence estimation (DFSE) block; and
a prefilter disposed between the DFSE block and the SAIR block.

46. The receiving system of claim 38 wherein the selection subsystem further comprises:

15 a metric calculator connected to the STIW block; and
a metric comparator connected to the metric calculator and the timing selector.

47. The receiving system of claim 39 wherein the selection subsystem further comprises:

20 a metric calculator connected to the STIW block; and
a metric comparator connected to the metric calculator and the timing selector.

48. The receiving system of claim 40 wherein the selection subsystem further comprises:

25 a metric calculator connected to the STIW block; and

a metric comparator connected to the metric calculator and the timing selector.

49. The receiving system of claim 41 wherein the selection subsystem further comprises:

- 5 a metric calculator connected to the STIW block; and
- a metric comparator connected to the metric calculator and the timing selector.

50. The receiving system of claim 42 wherein the selection subsystem further comprises:

- 10 a metric calculator connected to the STIW block; and
- a metric comparator connected to the metric calculator and the timing selector.

51. The receiving system of claim 43 wherein the selection subsystem further comprises:

- 15 a metric calculator connected to the STIW block; and
- a metric comparator connected to the metric calculator and the timing selector.

52. The receiving system of claim 44 wherein the selection subsystem further comprises:

- 20 a metric calculator connected to the STIW block; and
- a metric comparator connected to the metric calculator and the timing selector.

53. The receiving system of claim 45 wherein the selection subsystem further comprises:

- 25 a metric calculator connected to the STIW block; and
- a metric comparator connected to the metric calculator and the timing selector.

54. A processor-controlled receiving system comprising:

demodulation logic; and

a interference whitening synchronization block preceding the demodulation logic, the interference whitening synchronization block disposed to receive a received signal and further comprising:

synchronization and channel estimation logic for producing a plurality of signal samples from the received signal;

a comparator and selector block connected to the joint timing and channel estimation block;

a spatio-temporal interference whitening (STIW) block connected to the comparator and selector block, the STIW block for applying spatio-temporal interference whitening to each of the plurality of signal samples to produce a plurality of whitened signal samples; and

a selection subsystem connected to the timing selector and the STIW block, the selection subsystem operable to determine a best whitened signal sample from among the plurality of whitened signal samples based on channel estimates and on a relative, minimum value of a specified metric and for synchronizing the receiver with the received signal based on timing of the best whitened signal sample.

55. The receiving system of claim 54 further comprising a single antenna interference rejection (SAIR) block disposed between the interference whitening synchronization block and the demodulation logic, the SAIR block for determining time-varying channel parameters and applying a whitening filter to the received signal based on a frequency offset between the received signal and an interfering signal.

56. The receiving system of claim 54 wherein the STIW block is a single antenna interference rejection (SAIR) block for determining time-varying channel

parameters and applying a whitening filter to the received signal based on a frequency offset between the received signal and an interfering signal.

57. The receiving system of claim 55 wherein the demodulation logic further comprises:

- 5 a decision feedback sequence estimation (DFSE) block; and
 a prefilter disposed between the DFSE block and the SAIR block.

58. The receiving system of claim 40 wherein the demodulation logic further comprises further comprises a maximum likelihood sequence estimation (MLSE) block.

- 10 59. The receiving system of claim 41 wherein the demodulation logic further comprises further comprises a maximum likelihood sequence estimation (MLSE) block.

- 15 60. The receiving system of claim 48 wherein the demodulation logic further comprises further comprises a maximum likelihood sequence estimation (MLSE) block.

61. The receiving system of claim 49 wherein the demodulation logic further comprises further comprises a maximum likelihood sequence estimation (MLSE) block.


- 20 62. The receiving system of claim 55 wherein the demodulation logic further comprises further comprises a maximum likelihood sequence estimation (MLSE) block.

63. The receiving system of claim 40 wherein the SAIR block also serves as the STIW block.

64. The receiving system of claim 41 wherein the SAIR block also serves as the STIW block.

65. The receiving system of claim 55 wherein the SAIR block also serves as the STIW block.

FIG. 1



Amplitude



FIG. 2
Prior Art**FIG. 3**
Prior Art

FIG. 4




FIG. 5




FIG. 6




FIG. 8




FIG. 7




FIG. 9




FIG. 10




FIG. 11




FIG. 12




FIG. 13




FIG. 14






FIG. 15
Prior Art



Different sampling hypotheses
within a symbol
1503



A sampling
and timing
hypothesis
1502

FIG. 16




FIG. 17




FIG. 18





FIG. 19








FIG. 22



INTERNATIONAL SEARCH REPORT

International application No.

PCT/US 02/25848

A. CLASSIFICATION OF SUBJECT MATTER

IPC 7 H04L25/03 H04B7/005 H04B1/12

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H04L H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, PAJ, WPI Data

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	WO 99 65160 A (ITALTEL SPA ; FANFONI SABINA (IT); PICCIRIELLO AGOSTINO (IT); SPAGN) 16 December 1999 (1999-12-16) page 1, line 8 -page 25, line 2; figures 1-5, 12	1-16, 22, 24-26, 35, 38-65
A	WO 00 64061 A (ERICSSON TELEFON AB L M) 26 October 2000 (2000-10-26) page 1, line 9 -page 9, line 7; figure 2	1-65
A	US 5 231 648 A (DRIEDGER MARK E ET AL) 27 July 1993 (1993-07-27)	



Further documents are listed in the continuation of box C.



Patent family members are listed in annex.

* Special categories of cited documents:

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

T later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

X document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

Y document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

G document member of the same patent family

Date of the actual completion of the international search

31 October 2002

Date of mailing of the international search report

07/11/2002

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Andersen, J.G.

INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No.

PCT/US 02/25848

Patent document cited in search report		Publication date		Patent family member(s)	Publication date
WO 9965160	A	16-12-1999	IT	MI981280 A1	06-12-1999
			CA	2334153 A1	16-12-1999
			WO	9965160 A1	16-12-1999
			EP	1084536 A1	21-03-2001
WO 0064061	A	26-10-2000	AU	4631400 A	02-11-2000
			CN	1355959 T	26-06-2002
			EP	1190491 A1	27-03-2002
			WO	0064061 A1	26-10-2000
			SE	9901384 A	17-10-2000
US 5231648	A	27-07-1993	CA	2061851 A1	22-09-1992